

Is Now Part of



## **ON Semiconductor**®

# To learn more about ON Semiconductor, please visit our website at <u>www.onsemi.com</u>

Please note: As part of the Fairchild Semiconductor integration, some of the Fairchild orderable part numbers will need to change in order to meet ON Semiconductor's system requirements. Since the ON Semiconductor product management systems do not have the ability to manage part nomenclature that utilizes an underscore (\_), the underscore (\_) in the Fairchild part numbers will be changed to a dash (-). This document may contain device numbers with an underscore (\_). Please check the ON Semiconductor website to verify the updated device numbers. The most current and up-to-date ordering information can be found at <a href="mailto:www.onsemi.com">www.onsemi.com</a>. Please email any questions regarding the system integration to <a href="mailto:Fairchild\_questions@onsemi.com">Fairchild\_questions@onsemi.com</a>.

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or unavteries, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out or i, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that ON Semiconductor was negligent regarding the design or manufacture of the part. ON Semiconductor and is officers, employees, uniotificated use, even if such claim any manner.



## FDB024N06 N 沟道 PowerTrench<sup>®</sup> MOSFET 60 V, 265 A, 2.4 mΩ

### 特性


- $R_{DS(on)}$  = 1.8 m $\Omega$  (Typ.)@V<sub>GS</sub> = 10 V, I<sub>D</sub> = 75 A
- 快速开关速度
- 低栅极电荷
- 高性能沟道技术可实现极低的 R<sub>DS(on)</sub>
- 高功率和高电流处理能力
- ・ 符合 RoHS 标准


### 说明

此 N 沟道 MOSFET 采用飞兆半导体先进的 PowerTrench<sup>®</sup> 工艺 生产,这一先进工艺是专为最大限度地降低导通电阻并保持卓越 开关性能而定制的。

### 应用

- 用于 ATX/ 服务器 / 电信 PSU 的同步整流
- 电池保护电路
- 电机驱动和不间断电源
- 可再生系统





### MOSFET 最大额定值 Tc=25°C 除非另有说明。

符号			FDB024N06	单位	
V <sub>DSS</sub>	漏极一源极电压			60	V
V <sub>GSS</sub>	栅极一源极电压			±20	V
	-	连续 (T <sub>C</sub> = 25°C,硅限制)	2	265	
I <sub>D</sub> 漏极电	漏极电流 -	- 连续(T <sub>C</sub> = 100°C,硅限制)		190	Α
	-	连续 (T <sub>C</sub> = 25°C, 封装限制)		120	
I <sub>DM</sub>	漏极电流 -	脉冲 (	注 1)	1060	Α
E <sub>AS</sub>	单脉冲雪崩能量	(	注2)	2531	mJ
dv/dt	峰值二极管恢复 dv/dt	(	注 3)	6.0	V/ns
P <sub>D</sub> 功非		T <sub>C</sub> = 25°C)		395	W
	切耗 -	降低至 25°C 以上		2.6	W/°C
T <sub>J</sub> , T <sub>STG</sub>	工作和存储温度范围			-55 ? +175	°C
TL	用于焊接的最大引线温度,距离外壳 1/8",持续 5 秒			300	°C


### 热性能


符号	参数	FDB024N06	单位
$R_{\theta JC}$	结至外壳热阻最大值。	0.38	
D	结至环境热阻 (最小尺寸的 2 盎司焊盘)最大值。	62.5	°C/W
$R_{ extsf{ heta}JA}$	结至环境热阻 (1 in <sup>2</sup> 2 盎司焊盘)最大值。	40	

2014年1月

器件编号 FDB024N06		<b>顶标 封</b> 筆 FDB024N06 D <sup>2</sup> -P		<b>包装方法</b> 卷带	<b>卷尺寸</b> 330 mm		<b>带宽</b> 4 mm		
电气特性	T <sub>C</sub> = 25°C	) 除非另有说明。							
符号				测试条件	<b>‡</b>	最小值	典型值	最大值	单位
关断特性		~~~~		(A) #4351	•				
	22-11 22	5선수 승수 대				60			V
BV <sub>DSS</sub> ∆BV <sub>DSS</sub>	<b>漏</b> 极一游	原极击穿电压		I <sub>D</sub> = 250 μA, V <sub>GS</sub> = 0 V		60	-	-	
ΔDV <sub>DSS</sub> / ΔTJ	击穿电压	温度系数		I <sub>D</sub> = 250 μA,参考 25	5°C	-	0.04	-	V/°C
		<b>正</b> 泪却去法		V <sub>DS</sub> = 60 V, V <sub>GS</sub> = 0 V		-	-	1	
DSS	零栅极电	且压漏极电流		$V_{DS} = 60 \text{ V}, V_{GS} = 0$	V, T <sub>C</sub> = 150°C	-	-	500	μA
I <sub>GSS</sub>	栅极 - 体	漏电流		$V_{GS}$ = ±20 V, $V_{DS}$ = (	) V	-	-	±100	nA
导通特性									
V <sub>GS(th)</sub>	栅极阈值	自用压		V <sub>GS</sub> = V <sub>DS</sub> , I <sub>D</sub> = 250	μA	2.5	3.5	4.5	V
R <sub>DS(on)</sub>		原极静态导通电阻		$V_{GS} = 10 \text{ V}, I_D = 75 \text{ A}$		-	1.8	2.4	mΩ
9 <sub>FS</sub>	正向跨导			$V_{DS} = 10 \text{ V}, \text{ I}_{D} = 75 \text{ A}$		-	200		S
动态特性									
C <sub>iss</sub>	输入电容				-	11190	14885	pF	
C <sub>oss</sub>	输出电容			$V_{DS} = 25 \text{ V}, \text{ V}_{GS} = 0 \text{ V},$ f = 1 MHz		_	1610	2140	pF
C <sub>rss</sub>	反向传输					-	750	1125	pF
Q <sub>g(tot)</sub>		册极电荷总量		V <sub>DS</sub> = 48 V, I <sub>D</sub> = 75 A, V <sub>GS</sub> = 10 V		-	174	226	nC
Q <sub>gs</sub>						-	54	-	nC
Q <sub>gd</sub>				(说明4)		-	50	-	nC
 开关特性				1		I			
t <sub>d(on)</sub>	导通延迟	时间				_	134	278	ns
t <sub>r</sub>	开通上升			V <sub>DD</sub> = 30 V, I <sub>D</sub> = 75 A	۹,	-	324	658	ns
t <sub>d(off)</sub>	关断延迟			V <sub>GS</sub> = 10 V, R <sub>G</sub> = 25		-	348	706	ns
t <sub>f</sub>	关断下降时间					250	510	ns	
, 漏极 - 源极					(说明 4)				
I <sub>S</sub>	<b>x — 1                                  </b>					-	-	265	Α
I <sub>SM</sub>	漏极 - 源极二极管最大正向脉冲电流						-	1060	Α
V <sub>SD</sub>	漏极 - 源极二极管正向电压		2.000	V <sub>GS</sub> = 0 V, I <sub>SD</sub> = 75 A		-	-	1.3	V
t <sub>rr</sub>	反向恢复			V <sub>GS</sub> = 0 V, I <sub>SD</sub> = 75 A		-	69	-	ns
Q <sub>rr</sub>	反向恢复			$dI_F/dt = 100 A/\mu s$		-	152	-	nC


### 典型性能特征







FDB024N06 —

N 沟道 PowerTrench<sup>®</sup> MOSFET







7



SEMICONDUCTOR

#### TRADEMARKS

The following includes registered and unregistered trademarks and service marks, owned by Fairchild Semiconductor and/or its global subsidiaries, and is not intended to be an exhaustive list of all such trademarks

interfueu to be an exhaustive list of	an such hauchlaiks.		
AccuPower™ AX-CAP <sup>®</sup> * BitSiC™ Build it Now™	F-PFS™ FRFET <sup>®</sup> Global Power Resource <sup>SM</sup> GreenBridge™	O® PowerTrench <sup>®</sup> PowerXS™	Sync-Lock™ SYSTEM <sup>®*</sup> GENERAL TinyBoost <sup>®</sup>
Build it Now™ CorePLUS™ CorePOWER™ CROSSVOLT™ CTL™ Current Transfer Logic™ DEUXPEED® Dual Cool™ EcoSPARK® EfficentMax™ ESBC™ Fairchild® Fairchild® Fairchild Semiconductor® FACT Quiet Series™ FACT® FAST®	GreenBridge™ Green FPS™ e-Series™ <i>Gmax</i> ™ GTO™ IntelliMAX™ ISOPLANAR™ Marking Small Speakers Sound Loude and Better™ MegaBuck™ MICROCOUPLER™ MicroPat™ MicroPak™ MicroPak™ MicroPak™ MicroPak™ OroPak™ OtoInMax™ mWSaver <sup>®</sup> OptoHIT™	Programmable Active Droop™ QFET <sup>®</sup> QS™ Quiet Series™ RapidConfigure™	TinyBoost <sup>®</sup> TinyBoost <sup>®</sup> TinyCalc <sup>™</sup> TinyLogic <sup>®</sup> TiNYOPTO <sup>™</sup> TinyPWM <sup>™</sup> TinyWire <sup>™</sup> TranSiC <sup>™</sup> TriFault Detect <sup>™</sup> TRUECURRENT <sup>®</sup> * µSerDes <sup>™</sup> UHC <sup>®</sup> Ultra FRFET <sup>™</sup> UniFET <sup>™</sup>
FastvCore™ FETBench™ FPS™	OPTOLOGIC® OPTOPLANAR®	SuperSOT™-8 SupreMOS <sup>®</sup> SyncFET™	VCX™ VisualMax™ VoltagePlus™ XS™

\*Trademarks of System General Corporation, used under license by Fairchild Semiconductor.

#### DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

LIFE SUPPORT POLICY FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used here in:

- Life support devices or systems are devices or systems which, (a) are 1. intended for surgical implant into the body or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
- 2. A critical component in any component of a life support, device, or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

#### ANTI-COUNTERFEITING POLICY

Fairchild Semiconductor Corporation's Anti-Counterfeiting Policy. Fairchild's Anti-Counterfeiting Policy is also stated on our external website, www.Fairchildsemi.com, under Sales Support.

Counterfeiting of semiconductor parts is a growing problem in the industry. All manufactures of semiconductor products are experiencing counterfeiting of their parts. Customers who inadvertently purchase counterfeit parts experience many problems such as loss of brand reputation, substandard performance, failed application, and increased cost of production and manufacturing delays. Fairchild is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. Fairchild strongly encourages customers to purchase Fairchild parts either directly from Fairchild or from Authorized Fairchild Distributors who are listed by country on our web page cited above. Products customers buy either from Fairchild directly or from Authorized Fairchild Distributors are genuine parts, have full traceability, meet Fairchild's quality standards for handing and storage and provide access to Fairchild's full range of up-to-date technical and product information. Fairchild and our Authorized Distributors will stand behind all warranties and will appropriately address and warranty issues that may arise. Fairchild will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. Fairchild is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.

#### PRODUCT STATUS DEFINITIONS Definition of Terms

Datasheet Identification	Product Status	Definition
Advance Information	Formative / In Design	Datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	Datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.
No Identification Needed	Full Production	Datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve the design.
Obsolete	Not In Production	Datasheet contains specifications on a product that is discontinued by Fairchild Semiconductor. The datasheet is for reference information only.

ON Semiconductor and are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at <u>www.onsemi.com/site/pdf/Patent-Marking.pdf</u>. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor has against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death ass

#### PUBLICATION ORDERING INFORMATION

#### LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor 19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada Europe, Middle East and Africa Technical Support: Phone: 421 33 790 2910

Japan Customer Focus Center Phone: 81-3-5817-1050 ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative

© Semiconductor Components Industries, LLC