

SHARP

SYSTEM DEVICE UNIT ELECTRONIC COMPONENTS AND DEVICES DIVISION SHARP CORPORATION

SPECIFICATION

DEVICE SPECIFICATION FOR

PHOTOCOUPLER

MODEL No.

PC851

(Business dealing name : PC851XNNIP9F)

Specified for

Enclosed please find copies of the Specifications which consists of 14 pages including cover. This specification sheets and attached sheets shall be both side copy. After confirmation of the contents, please be sure to send back copies of the Specifications with approving signature on each.

CUSTOMER'S APPROVAL

DATE

BY

PRESENTED

DATE

BY

T. Ichinose, Department General Manager of Development Dept. II System Device Unit Electronic Components and Devices Division SHARP CORPORATION

Product name : PHOTOCOUPLER

Model No.: PC851

(Business dealing name : PC851XNNIP9F)

Γ

	These specification sheets include materials protected under copyright of Sharp Corporation ("Sharp"). Please do not reproduce or cause anyone to reproduce them without Sharp's consent.
	When using this product, please observe the absolute maximum ratings and the instructions for use outlined in these specification sheets, as well as the precautions mentioned below. Sharp assumes no responsibility for any damage resulting from use of the product which does not comply with the absolute maximum ratings and the instructions included in these specification sheets, and the precautions mentioned below.
	 (Precautions) (1) Please do verify the validity of this part after assembling it in customer's products, when customer wants to make catalogue and instruction manual based on the specification sheet of this part. (2) This product is designed for use in the following application areas ; ·OA equipment Audio visual equipment ·Home appliances ·Telecommunication equipment (Terminal) ·Measuring equipment ·Tooling machines ·Computers If the use of the product in the above application areas is for equipment listed in paragraphs (3) or (4), please be sure to observe the precautions given in those respective paragraphs. (3) Appropriate measures, such as fail-safe design and redundant design considering the safety design of the overall system and equipment, should be taken to ensure reliability and safety when this product is used for equipment (aircraft, train, automobile etc.) ·Transportation control and safety equipment (aircraft, train, automobile etc.) ·Traffic signals ·Gas leakage sensor breakers ·Rescue and security equipment ·Other safety equipment (4) Please do not use this product for equipment which require extremely high reliability and safety in function and precision, such as ; ·Space equipment ·Telecommunication equipment (for trunk lines) ·Nuclear power control equipment ·Medical equipment ·Nuclear power control equipment ·Medical equipment (5) Please contact and consult with a Sharp sales representative if there are any questions regarding interpretation of the above four paragraphs.
3.	Please contact and consult with a Sharp sales representative for any questions about this product.
[W Th cus [W SH wa (1) (2)	Warranty term and warranty limits 'arranty term] e warranty term for the shipped product shall be for 1 year after shipping to the designated place by the ordered stomer. 'arranty limits] IARP supplies the replacement when this SHARP product shall be failed by SHARP's responsibility during above rranty term. However, this warranty is excluded in case of the following. In case of improper handling and using by the customer. In case of that the cause of the failure is caused by the reason other than this SHARP product. In case of modification and repairing by person other than SHARP responsibility is not for SHARP.

(4) In case of a calamity, a disaster and such as the case when that responsibility is not for SHARP.

This warranty herein means the warranty for this SHARP product itself, SHARP takes no responsibility for any damage caused by the failure of this SHARP product.

1. Application

This specification applies to the outline and characteristics of photocoupler Model No. PC851. (Lead free and Halogen free type).

2.	Outline	Refer to the attached sheet, page 4.
3.	Ratings and characteristics	Refer to the attached sheet, page 5, 6.
4.	Reliability	Refer to the attached sheet, page 7.
5.	Outgoing inspection	Refer to the attached sheet, page 8.

6. Supplement

- 6.1 Isolation voltage shall be measured in the following method.
 - (1) Short between anode and cathode on the primary side and between collector and emitter on the secondary side.
 - (2) The dielectric withstanding tester with zero-cross circuit shall be used.
 - (3) The wave form of applied voltage shall be a sine wave.(It is recommended that the isolation voltage be measured in insulation oil.)
- 6.2 Package specifications Refer to the attached sheet, page 9 to 11.
- 6.3 The business dealing name used for this product when ordered or delivered shall be PC851XNNIP9F.
- 6.4 This product is going to be approved by UL.
- 6.5 This product is not designed against irradiation.This product is assembled with electrical input and output.This product incorporates non-coherent light emitting diode.
- 6.6 ODS materials

This product shall not contain the following materials.

- Also, the following materials shall not be used in the production process for this product. Materials for ODS : CFC_s, Halon, Carbon tetrachloride, 1.1.1-Trichloroethane (Methyl chloroform)
- 6.7 Specified brominated flame retardants Specified brominated flame retardants (PBB and PBDE) are not used in this device at all.

6.8 Compliance with each regulation

(1) The RoHS directive (2002/95/EC)

This product complies with the RoHS directive (2002/95/EC) .

Object substances: mercury, lead, cadmium, hexavalent chromium, polybrominated biphenyls (PBB)

and polybrominated diphenyl ethers (PBDE)

(2) Content of six substances specified in Management Methods for Control of Pollution Caused by Electronic Information

Products Regulation (Chinese:电子信息产品污染控制管理办法).

	Toxic and hazardous substances					
Category	Lead (Pb)	Mercury (Hg)	Cadmium (Cd)	Hexavalent chromium (Cr ⁶⁺)	Polybrominated biphenyls (PBB)	Polybrominated diphenyl ethers (PBDE)
Photocoupler	\	1	1	\	1	1

✓: indicates that the content of the toxic and hazardous substance in all the homogeneous materials of the part is below the concentration limit requirement as described in SJ/T 11363-2006 standard.

(3) This product complies with "Halogen free".

"Halogen free" about this product is defined as follows.

The concentration ratio of Chlorinate and Bromine in raw material and indirect material, finished product can not exceed 900 ppm, the total concentration of the 2 substance should not exceed 1500 ppm.


7. Notes

Precautions for photocouplers : Attachment-1

(Notice)

The contents described herein are subject to change without notice for improvement since this product is under development.

2. Outline



3. Ratings and characteristics

3.1 Absolute maximum ratings

Absolute ma	ximum ratings			Ta=25°C
	Parameter	Symbol	Rating	Unit
	Forward current	$I_{\rm F}$	50	mA
Inmut	*1 Peak forward current	I _{FM}	1	А
Input	Reverse voltage	V _R	6	V
	Power dissipation	Р	70	mW
	Collector-emitter voltage	V _{CEO}	350	V
Orthurst	Emitter-collector voltage	V _{ECO}	6	V
Output	Collector current	I _c	50	mA
	Collector power dissipation	Pc	150	mW
	Total power dissipation	P _{tot}	200	mW
	Operating temperature	T _{opr}	-25 to +100	°C
Storage temperature *2 Isolation voltage *3 Soldering temperature		T _{stg}	-55 to +125	°C
		V _{iso(rms)}	5	kV
		T _{sol}	270	°C

REFERENCE

*1 Pulse width $\leq 100 \,\mu$ s, Duty ratio : 0.001.

*2 AC For $1 \min$, 40 to 60% RH

Isolation voltage shall be measured using the following method.


(1) Short between anode and cathode on the primary side and between collector and emitter on the

secondary side.

- (2) The isolation voltage tester with zero-cross circuit shall be used.
- (3) The waveform of applied voltage shall be a sine wave.
- *3 For 10s
- Electro-optical characteristics 3.2

Electro-optical characteristics Ta=25°C							
	Parameter	Symbol	Condition	MIN.	TYP.	MAX.	Unit
	Forward voltage	Forward voltage V_F $I_F=20mA$		-	1.2	1.4	V
Input	Reverse current	I _R	V _R =4V	-	-	10	$\mu \mathbf{A}$
	Terminal capacitance	Ct	V=0, f=1kHz	-	30	250	pF
	Dark current	I _{CEO}	V _{CE} =200V, I _F =0	-	I	1	$\mu \mathbf{A}$
Output	Collector-emitter breakdown voltage	BV _{CEO}	I_=0.1mA I_F=0	350	I	-	V
	Emitter-collector breakdown voltage	BV _{ECO}	$I_{E}=10 \ \mu \text{ A}, I_{F}=0$	6	-	-	V
	Collector current	Ic	$I_{\rm F}=5{\rm mA}, V_{\rm CE}=5{\rm V}$	2	I	-	mA
	*4 Current Transfer Ratio	CTR	$I_{\rm F}$ –JIIIA, V _{CE} –JV	40	I	-	%
	Collector-emitter saturation voltage	V _{CE(sat)}	I _F =20mA I _c =1mA	-	0.1	0.3	V
Transfer	Isolation resistance	R _{ISO}	DC500V 40 to 60%RH	5×10 ¹⁰	10 ¹¹	-	Ω
charac-	Floating capacitance	C _f	V=0, f=1MHz	-	0.6	1.0	pF
teristics	Cut-off frequency	$\mathbf{f}_{\mathbf{c}}$	$V_{CE}=5V, I_{c}=2mA$ R _L =100 \Omega, -3dB	-	50	-	kHz
	Rise time	tr	V _{CE} =2V I _c =2mA	-	4	10	μ s
	Fall time	$t_{\rm f}$	$R_L=100\Omega$	-	5	12	μ s

*4 CTR (%) = $(I_c / I_F) \times 100$



4. Reliability

The reliability of products shall satisfy items listed below.

Test item as require

Test title	Test condition
Temperature cycling test	Ta=-55 \sim 125°C, Dwell time=15min per zone, 100 cycles
High temperature operation life test	Ta=25°C, I _F =20mA, I _C =30mA, 1000h
High temperature reverse bias test	Ta=110°C, V _{CE} =350V, 1000h
High temperature storage test	Ta=125°C, 1000h
Low temperature storage test	Ta=-55°C, 1000h

Spec limit of product

-				Ta=25°C	
Parameter	Symbol	Mesurement condition	MIN.	MAX.	Unit
Forward voltage	V _F	I _F =20mA	-	1.4	V
Reverse current	I _R	V _R =4V	-	10	μA
Dark current	I _{CEO}	V _{CE} =200V	-	1	μA
Collector-emitter breakdown voltage	BV _{CEO}	I _C =0.1mA	350	-	V
Emitter-collector breakdown voltage	BV _{ECO}	Ι _Ε =10μ Α	6		V
Collector-emitter saturation voltage	V _{CE(sat)}	I _F =20mA,I _C =1mA	-	0.3	V
Current Transfer Ratio	CTR	I _F =5mA,V _{CE} =5V	40	-	%

Reliability criteria

- 1. Reading value for each step test not over 50% Delta for $V_{\text{F}}, BV_{\text{CEO}}, BV_{\text{ECO}}$ and CTR parameter .
- 2. Reading value for each step test not over spec limit for I_R , I_{CEO} and $V_{CE(sat)}$ parameter.

5. Outgoing inspection

- 5.1 Inspection items
 - (1) Appearance

5.2 Sampling method and Inspection level

A single sampling plan, normal inspection level II based on ISO 2859 is applied. The AQL according to the inspection items are shown below.


Defect	Inspection item	AQL(%)
Major defect	Unreadable marking	0.15
Minor defect	Appearance defect except the above mentioned.	0.65

6.2 Packing specification

6.2.1 Package materials


Name	Materials
Reel	PS
Packing case (Inner box)	Demor
Packing case (Outer carton)	Paper

6.2.2 Carrier tape structure and dimensions



•	Dimensions list (Unit : min)					
	W	P ₀	P ₁	P ₂	Y	
	16.0±0.3	4.0±0.1	8.0±0.1	2.0±0.1	7.5±0.1	


6.2.3 Reel structure and dimensions




G




6.2.4 Direction of product insertion





6.2.5 Outer packing appearance




() : Reference dimensions



Precautions for Photocouplers

1 Cleaning


- (1) Solvent cleaning : Solvent temperature 45°C or less Immersion for 3 min or less
- (2) Ultrasonic cleaning : The effect to device by ultrasonic cleaning differs by cleaning bath size, ultrasonic power output, cleaning time, PCB size or device mounting condition etc. Please test it in actual using condition and confirm that any defect doesn't occur before starting the ultrasonic cleaning.
- (3) Applicable solvent : Ethyl alcohol, Methyl alcohol, Isopropyl alcohol
 When the other solvent is used, there are cases that the packaging resin is eroded.
 Please use the other solvent after thorough confirmation is performed in actual using condition.
- 2. Circuit design
 - 2.1 The LED used in the Photocoupler generally decreases the light emission power by operation. In case of long operation time, please design the circuit in consideration of the degradation of the light emission power of the LED. (50%/5years)
 - 2.2 There are cases that the deviation of the CTR and the degradation of the relative light emission power of the LED increase when the setting value of I_F is less than 1.0mA. Please design the circuit in consideration of this point.
- 3. Precautions for Soldering
 - (1) In the case of flow soldering (Avoid immersing units body in the solder) One time soldering is recommended within the condition of temperature. Temperature: 260+0/-5°C Time: 10 s.
 Preheat temperature:25 to 140°C Preheat time: 30 to 80 s



(2) In the case of IR Reflow soldering

One time soldering reflow is recommended within the condition of temperature and time profile shown below.

Profile item	Conditions
Preheat • Temperature Min (Tsmin) • Temperature Max (Tsmax) • Time (Min to Max) (ts)	150℃ 200℃ 90±30 s
Soldering zone • Temperature (TL) • Time (tL)	217°C 60 s
Peak Temperature (TP)	260°C
Ramp-up rate	3°C/ s (Max)
Ramp-down rate	3 ~ 6℃/s



- (3) In the case of hand soldering by soldering iron
 Allow single lead soldering in every single process. One time soldering is recommended.
 Temperature: 380+0/-5°C
 Time: (max.) 3s
- (4) Other precautions
 - Avoid immersing units body in the solder
 - Depending on equipment and soldering conditions (temperature, Using solder etc.), the effect to the device and the PCB is different.

Please confirm that there is no problem on the actual use conditions in advance.