

吸锡线(带)

原装强力低残渣吸锡线

Place the wick over the solder to be removed. Push the heated soldering iron tip onto the wick. The melted solder will be absorbed.
Remove both the soldering wick and the soldering iron tip from the PCB.



专注品质 专注品牌

产品参数

PRODUCT PARAMETERS



1.5m×3.5mm
1.5m×2.5mm
1.5m×3.0mm
1.5m×2.0mm
1.5m×1.5mm

【产品名称】 维修佬原装吸锡线

【型号】 1515 2015 2515 3015 3515

【配置】 采用纯铜加特别化学配方配置而成

【产品包装】 8个/袋

【总长度】 1.5m×1.5/2.0/2.5/3.0/3.5mm

【产地】 广东深圳

【储存方法】 密封避光、干燥防潮

【特效】 耐氧化 防腐蚀 导热上锡性能好且彻底

【适用范围】 适用于清理PCB板等焊锡时使用

使用方法:
第一步: 对于想清除的焊锡,将适当长度的吸锡线置于被清理的回焊点上,然后用电烙铁焊嘴轻压加热。焊锡融化后即被吸锡线吸取。
Place the wick over the solder to be removed. Push the heated soldering iron tip onto the wick. The melted solder will be absorbed.

第二步: 一旦吸取了焊锡,请同时移开电烙铁和吸锡线。
Remove both the soldering wick and the soldering iron tip from the PCB.

第三步: 已使用过的吸锡线,请用剪钳剪掉。
Use nippers to cut off the used part of the wick.

用途举例：



注意：为防止烫伤，在使用过程中，请不要直接接触吸锡线，应拿住外壳或用镊子等工具夹取。

TO AVOID SOLDERING INJURY, DON'T HOLD THE DESOLDERING WICK DIRECTLY YOU SHOULD HOLD THE SHELL OR TAKE THE WIRE BY THE TWEEZERS OR OTHER TOOLS.

